user manual

QK-INT

AUDIO INTERCOM (5 wires)









General:

The 5 wires panel is an intercom system, serves as a door panel.

The main advantage of the system is that the panel doesn't require a special design handset for the system and can work with any standard 5 wires handset.

With this unit you can speak with the visitor who is waiting at

the door and open the electric lock from the intercom handset.

An optional bypass pushbutton enables easy internal opening (the opening time is programmable)

Features:

Easy installation, programming and	optional bypass exit pushbutton
operating.	
Surface and flush mount installation available	Environmental and anti vandal resistance.

Specifications:

Operating voltage: AC 12V 800mA	
Operating electric or magnetic lock. (normally	Opening time: 1-9 seconds
open)	
Color: bronze	Size: On the wall 154X100X35mm (H*W*D)

Installing the panel:

Install the lock in the door frame.

Using a Phillips screwdriver open the top cover, carefully pull up the panel.

Using a screw driver, expose the 4 covered insulations bores and the round wirings bore.

Attach the base of the Intercom Encoder to the wall, using a pencil mark the 4 fixing points. Drill the 4 fixing points on the wall.

Route the wires through the round bore in the base of the Intercom Encoder.

Using 4 screws install the base to the wall.



Reassemble the panel over the base. Attach the top cover to the base using the 4 screws.

Microphone and speaker volume adjustments

The QK-INT comes from the manufacture with default optimal state.

Sometimes because of the location (opened or closed space), acoustical problems occur. If the external unit speaker sound level is too high or low, gently rotate the internal **SP** potentiometer. (Clockwise to lower volume)

If the sound level in the handset is too high or low, gently rotate the internal MIC potentiometer. (Clockwise to lower volume)

Electrical Drawing external unit Microphone To avoid volume noises, The adjustment connection Relay between the power supply must be at this connection point on the Speaker volume PCB adjustment CO AC 12V AC Lock Power Supply Audio Interphone Handset COM 6 Lock 9 Buzzer ΒZ SP 1 2 MIC



QUIKO ITALY

Via Seccalegno, 19 36040 Sossano (VI) - Italy Tel. +39 0444 785513 Fax +39 0444 782371 info@quiko.biz www.quikoitaly.com

CE

The Manufacturer can technically improve the quality of its products without any prior notice.

ll Fabbricante può apportare ai suoi prodotti modifiche tecniche, migliorative della qualità, senza preavviso.